

# / AVR 660

7 x 75W 7.1-Channel A/V receiver with HDMI™ 1.3a repeater, audio/video processing and upscaling to 1080p



## Highlights

- Dolby TrueHD processing
- Logic 7® (5.1 and 7.1) processing
- Dolby Volume technology
- DTS®-HD Master Audio™ processing
- HDMI repeater with 1080p upscaling
- Faroudja DCDi Cinema™ video processing
- EzSet/EQ™ equalization
- iPod-ready
- HDTV-ready
- Component video inputs
- Quadruple-crossover bass manager
- RS-232 control connection
- Multiroom audio
- High-current capability
- 192kHz/24-Bit DACs
- USB input
- Internet radio

With Dolby Volume technology that automatically adjusts volume levels when you switch between sources and channels, four HDMI inputs, Faroudja DCDi Cinema video processing, all the latest Dolby and DTS audio modes, our own Logic 7 processing, the EzSet/EQ system for precise room calibration, and both USB and iPod connectivity, the AVR 660 is an unusually versatile performer, and its full-color graphical interface makes it an exceptionally friendly one. The AVR 660 easily enables multizone audio setups. It automatically corrects annoying “lip sync” problems with both HDMI Lip Sync capability and manual A/V Sync Delay. Front-panel A/V inputs make video gaming more convenient (not to mention more exciting). And an eight-device learning and programmable remote puts all of the AVR 660’s capabilities at your fingertips.

## Key Specifications

- Audio Section – Continuous Average Power (FTC), (stereo mode): 85 watts per channel into 8 ohms @ 20Hz – 20kHz, <0.07% THD, both channels driven; (seven-channel surround mode): 75 watts per channel into 8 ohms @ 20Hz – 20kHz, <0.07% THD, all channels driven; High Instantaneous Current capability (HCC): ±50 amps
- Tuner – Usable Sensitivity: IHF 1.3µV/13.2dBf; THD at 1kHz with 100% modulation, (mono): 0.2%; (stereo): 0.3%; FM Adjacent Channel Selectivity: ±400kHz, 70dB; Ultimate (maximum) S/N Ratio (measured at 1mV RF input level), (mono): 70dB; (stereo): 68dB
- Dimensions (H x W x D) and weight: 165mm x 440mm x 420mm, 18.6kg

Depth measurement includes knobs, buttons and terminal connections, unless stated otherwise; height measurement includes feet and chassis, unless stated otherwise.

# / AVR 660

7 x 75W 7.1-Channel A/V receiver with HDMI™ 1.3a repeater, audio/video processing and upscaling to 1080p

## Features

### Power

- 75W x 7 into 8 ohms, 20Hz – 20kHz, at <0.07% THD, with all channels driven simultaneously
- High-current (±60 amps), ultrawide-bandwidth (10Hz – 100kHz) amplifier design

### Surround Processing

- Full suite of Dolby surround decoding, including Dolby Digital Plus and Dolby TrueHD using two advanced TI™ DA 710 32-bit DSP processors
- Full suite of DTS modes, including DTS-HD, DTS-HD Master Audio, DTS-ES® 6.1 Discrete & Matrix, DTS Neo:6® and DTS 96/24™
- Dolby Volume technology
- Dolby Pro Logic® IIx (Movie, Music and Game modes) surround sound
- Harman-exclusive Logic 7 Cinema and Music surround sound processing in 5.1 and 7.1 channels
- Dolby Headphone and Dolby Virtual Speaker surround modes
- Five- and seven-channel Stereo, Hall and Theater surround modes
- 192kHz/24-Bit DACs
- Compressed Music Tools improve playback quality of any compressed audio stream or Internet radio

### Connectivity

- Four HDMI 1.3a inputs and one HDMI output with 12-bit Deep Color and xvYCC pass-through
- Three assignable, wide-bandwidth (100MHz), HDTV-ready component video inputs and one output
- Connects to the Harman Kardon®-engineered The Bridge II docking station for iPod and iPhone playback, control and charging
- Two subwoofer outputs for direct connection to powered subwoofers
- Three A/V inputs with S-video, plus three audio-only inputs
- Eight-channel-direct inputs for use with external surround decoders
- 7.1 Preamp outputs allow the use of external amplifiers
- Convenient front-panel audio/video input with S-video for use with video games or portable players
- Eight digital inputs (three optical and three coaxial on rear panel, and one optical and one coaxial on front panel)
- Two digital outputs (one optical and one coaxial on rear panel)
- RS-232 port for system control
- Firmware upgrades via USB
- One USB input for playback of audio and JPEG image files from external memory devices
- Ethernet network connection for Internet radio

### Ease of Use

- HDMI 1.3a with audio processing and Faroudja DCDi Cinema video processing with upscaling to 1080p
- A/V Sync Delay adjustable for each input
- EzSet/EQ equalization for quick and accurate system setup
- Internet radio and FM stereo/FM/AM tuner with 30 presets and direct-access tuning
- Quadruple-crossover bass manager
- Wide range of low-frequency crossover points (40Hz, 60Hz, 80Hz, 100Hz, 120Hz and 200Hz) available
- Full-color, high-definition, graphical on-screen interface, including HDMI and component video
- Programmable power-up volume
- Multiroom audio with Zone II remote control, A-BUS® Ready
- Surround back amplifier channels configurable for use as second-zone amplification
- Detachable IEC power cord
- Eight-device, backlit, preprogrammed and learning system remote control

## H A Harman International Company

© 2008 Harman International Industries, Incorporated. All rights reserved. Harman Kardon and Logic 7 are trademarks of Harman International Industries, Incorporated, registered in the United States and/or other countries. Designed to Entertain and EzSet/EQ are trademarks of Harman International Industries, Incorporated. iPod is a trademark of Apple Inc., registered in the U.S. and other countries. iPhone is a trademark of Apple Inc. HDMI is a trademark or registered trademark of HDMI Licensing LLC. Dolby and Pro Logic are registered trademarks of Dolby Laboratories. DTS, DTS-ES and DTS Neo:6 are registered trademarks, and DTS-HD Master Audio and DTS 96/24 are trademarks of DTS, Inc. TI is a trademark of Texas Instruments. Faroudja DCDi Cinema is a trademark of Genesis Microchip Inc. A-BUS is a registered trademark of LeisureTech Electronics Pty Ltd.

Features, specifications and appearance are subject to change without notice.

EAN Code AVR 660/230: 0282925064064